

Thanks for purchasing my
BB Preamp Andy Timmons
Signature Series Pedal!
This pedal has been a
permanent part of my live
+ studio rig now for many
years.

-Andy



Xotic Effects.
CALIFORNIA

14920 Calvert Street • Van Nuys, CA 91411
xotic.us • info@xotic.us



"The volume is a little past 9:00, gain is pretty much straight up. I always back a little treble down to try and keep it warmer, and the bass is boosted just slightly."

S P E C S :

Dimensions (W/D/H): 4.39" x 2.38" x 1.98" (110mm X 60mm X 50mm)
Weight: 0.6 lbs. (270g)
True Bypass Switching
Power Consumption: 9VDC/15mA (max)
 Approx. 40hrs continuous use with alkaline battery
Battery Type: 9VDC (006P) x 1
AC Adapter (Optional): 9VDC Negative Tips (Regulated recommended)
 Boss PSA, Ibanez AC109, Dunlop Brick, Voodoo Labs, 1-spot etc
Input Impedance: 1M ohm
Output Impedance: 2K ohm

DC JACK
when an external power supply is used the battery is disconnected from the circuit. remove four screws from the bottom plate to access battery



TREBLE

BASS

INPUT JACK
(nominal input -20dbu)
unplug when it's not in use for a longer battery life

ON/OFF SWITCH

GAIN

VOLUME

OUTPUT JACK